# TSK PRODUCTS





#### PROTECTING WHAT'S IMPORTANT: THE SAFETY OF OUR PEOPLE AND THOSE AROUND THEM

To ensure that people entering your campus are not running a high temperature and exposing others to potential threats, TSK Products, Diversified and Aurora proudly introduce the new infrared temperature sensor, VitalSign. With an advanced algorithm for detecting and calculating heat signatures, VitalSign provides alerts when a person is running a high temperature within one second and from three feet away.

Based on trusted German technology, the highly accurate sensor measures with a tolerance of +/- 0.5 degrees Celsius (+/- 0.9 degrees Fahrenheit). Add this extra layer of safety to your facilities today to protect what's important tomorrow.



#### Why a temperature sensor?



Provides the first layer of screening protection

More hygienic with non-touch infrared technology

Multiple devices can be monitored by a single user












### **Options**

- APS-1 adjustable pole stand with weighted base
- WMT-1 VESA wall mount
- Future firmware upgrade options
  - Photo & thermal result email alerts
  - Facial recognition
  - Customized flagging
  - ReAX control
  - Integration with third-party control and access systems









#### **ABOUT TSK Products**

TSK Products started in 2000, led by an oncology nurse. We have been focused on safety and comfort in healthcare environments, ensure everyone in the facility is protected from infections with the use of UV lights. Our seating in infusion clinics has benefits for the patient with USB charging ports, heated seats, etc., and for nurses with ergonomic designs.

The VitalSign Tablets are designed to detect temperature anomalies. It's important to understand there are many factors, including environmental and physiological that can impact a person's surface temperature reading. Skin surface temperature vs actual core body temperature may differ either way. The VitalSign Tablets must be operated in accordance with the manufacturer's user guide. VitalSignTablets are not intended nor designed to diagnose or detect medical conditions including, but not limited to, viruses or other illnesses. The VitalSign Tablets should only be used to detect variations in surface temperature. In the event that an elevated skin temperature is detected, the subject should be advised to check temperature with an approved medical thermometer and the finding confirmed. Absence of an elevated skin temperature does not preclude a fever.



## **SPECIFICATIONS**

		TTS-10	TTS-15	TTS-21
Screen Size		10"	15.6"	21.5"
Panel Information	Resolution	1280 x 800	1920 x 1080	
	Brightness	350 cd/m²	250 cd/m²	
	Contrast Ratio	8000:1	1000:1	
	Aspect Ratio	16:10	16:9	
	Active Display Area	134.8 x 216.2mm	344.16 x 193.59mm	476.06 x 267.786mm
	Viewing Angle	H:170° / V:170°	H:178°	? / V:178°
	Touch Tech	5 point cap touch (6H semi-tempered glass)	glass) 10 point cap touch (reflective glass)	
Hardware & OS	CPU	RK3288 Cortex A17, Ouad core 1.8GHz		
	RAM	2GB DDR3		
	ROM	8GB eMMC Flash		
	OS		Android 7.1	
Video/Image	Video Format	H.265, VP8, RV, WMV, AVS, H.263, MPEG4, HTMLS, Flash 10	H.265, VP8, RV, WMV, AVS, H.263, MPEG4, Up to 4K2K decoding, HTML5, Flash 10	
	Audio Format	MP3 / WMA / AAC etc.		
	Image Format	JPEG, BMP, PNG		
Audio	Speaker	1W x 2	2W x 2	
Communication	Bluetooth	EDR 4.0		
	WiFi	802.11 b/g/n 2.4GHz and 5GHz		
	Ethernet	10/100 LAN		
General Information	Color	Black		
	1/0	RJ45 x 1, USB x 1; SD slot x I; Micro-USB x 1; 3.5mm audio x 1; Recover x 1; expandable 2 USB	RJ45 x 1; USB x 4; SD slot x 1; Micro-USB x 1; 3.5mm audio x 1; Recover x 1; GPIO Support	RJ45 x 1; USB x 4; SD slot x I; Micro-USB x 1; 3.5mm audio x 1; Recover x Recover x 1; RS232 x 2; GPIO Support
	AV Capability	Front Facing Camera 2 MP fixed focus		
	Included in Box	Tablet, Power Adapter, Power cable		
	Sensors	G-sensor		
	Consumption	11W	15W	32W
	Power Input	12V 2A or PoE (802.3at)	12V 5A	
	Operating Environment	Operating: 32°F to 100°F (0°C to 40°C); Storage: -4°F to 122°F (-20°C to 50°C) Operating: 20%-80%; Storage· 10%-95%		
	Certification	CE, FCC, ROHS		
	Language	Multi language		
	VESA 100	VESA 75	VESA 100	
	Warranty	2 Years		
Infrared Temperature Sensor	Power Input	3.3- 3.6V, 50mA, USB connect		
	Size	65.2mm x 38.5mm x 22mm		
	Temperature Check Distance	0.3m-1m		
	Temperature Check Range	86°F to 113°F (30°C to 45°C)		
	Temperature Check Error	+/-0.3°C @1 Hz (+/- 0.5°F)		
	Size (WxDxH)	267 x 34 x 165mm	383.8 x 223.2 x 30.1mm	534.5 x 326 x 47.6326mm
	Product Weight	700g	1.4Kg	3.8Kg
	Box Size	385 x 65 x 222mm	444 x 348 x 112mm	534.5 x 326.0 x 47.6mm



#### FREQUENTLY ASKED QUESTIONS

Q: How accurate is the infrared sensor?

A: +/- 0.3 degrees Celsius (+/- 0.5 degrees Fahrenheit).

Q: What is the scan distance?

A: 0.5 to 1 meter.

Q: What is the temperature detection speed?

A: 1 second.

Q: How many people can it detect one time?

A: 1 person can be scanned at a time.

Q: Is there an option to store the data of people checked? If yes, how far back?

A: Currently no. This will be a future option.

Q: Is the unit able to detect people of different heights (e.g. children, adults 3' to 6.5')?

A: There's a visible sensor and a camera that will show your face on the LCD screen. Within the effective scanning range, the sensor should pick up the face, though in extreme cases the tablet might need to be adjusted.

Q: Are there any data/tests available regarding the accuracy of this unit?

A: The accuracy is at 0.3 degrees Celsius (+/- 0.5 degrees Fahrenheit) which is provided by our component manufacturer located in Germany. For the past few months this module has been implemented with projects for access control.

Q: Can the sensor be affixed to a door, away from the tablet that collects data?

A: The sensor must be connected to the tablet at this time.

Q: Will the system detect objects and/or animals?

A: The system is designed to only detect people.

Q: How does the alert message work? Are there display and sound alerts?

A: On the display screen, it will show the person's face and current temperature. If it senses a temperature higher than what has been set as normal, the tablet will show red and emit an alert sound.

